NUMBER ONE IN HOME AUTOMATION AND SECURITY

Wireless Remote HR10™

- **Controls up to 16 lights and appliances by remote control.**
- **Works with any X-10 Transceiver (TM13) or any X-10 Security System to control X-10 Modules.**
- **Works with the X-10 ActiveHome Two-Way Computer Interface (IH3010) to initiate Macros.**
- **Up to 25 meters range.**

WIRELESS REMOTE CONTROL HR10 - SET UP AND OPERATING INSTRUCTIONS

The HR10 Remote Control sends Wireless Radio Frequency (RF) signals to an X-10 Transceiver (TM12 or TM13) or any X-10 security system base receiver. The receiver then passes the signals onto your house wiring to control lights or appliances around your home. You plug lights and appliances into X-10 Modules (sold separately). The Remote Control also works with the CM11 Two-Way Computer Interface to initiate macros (routines) so you can set up a “coming home” routine which is initiated when you press a button on the Remote Control.

1. Install 4 AAA alkaline batteries (sold separately) in the battery compartment.
2. Use a dime to set the Housecode dial to match the setting of the X-10 Modules you want to control.
3. Set the slide switch to 1-8 to control Modules set to Unit Codes 1 thru 8.
4. Set the slide switch to 9-16 to control Modules 9 thru 16.
5. Press the corresponding ON or OFF button to turn Modules on and off.
6. To brighten or dim lights connected to X-10 Lamp and Wall Switch Modules, first press the corresponding number button, then press the UP or DOWN (blue) buttons.

NOTE: NO CHANGES OR MODIFICATIONS MAY BE MADE TO THE UNITS. ANY CHANGES MADE TO THE UNITS WILL VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

Made in China